


USR-EV908J(RK3588)



Catalogue

| | |
|------------------------------------|----|
| 1. Product Overview | 3 |
| 2. Characteristic | 3 |
| 3. Product interface | 4 |
| 3.1. Hardware specifications | 5 |
| 3.2. structure size | 7 |
| 3.3. Source | 8 |
| 3.4. Screen backlight | 8 |
| 3.5. eDP | 9 |
| 3.6. electric fan | 9 |
| 3.7. LVDS | 9 |
| 3.8. MIPI Camera | 11 |
| 3.9. UART TTL | 12 |
| 3.10. Button/Remote Control | 12 |
| 3.11. DEBUG | 12 |
| 3.12. MIC | 12 |
| 3.13. suona | 13 |
| 3.14. I2C | 13 |
| 3.15. USB | 13 |
| 3.16. RTC | 14 |
| 3.17. CAN | 14 |
| 3.18. RS232/RS485 | 15 |
| 3.19. RS485 | 15 |
| 3.20. IO | 17 |
| 3.21. RJ45 | 17 |
| 3.22. FPC MiPi LCD | 19 |
| 3.23. POE | 20 |



1. Product Overview

The USR-EV908J-3588 motherboard features Rockchip's RK3588J industrial-grade octa-core 64-bit CPU with a clock speed up to 2.4GHz, supporting operating systems including Ubuntu, Android, and Debian while delivering exceptional general-purpose computing performance. It integrates a quad-core Mali-G610 GPU for robust graphics processing and a built-in AI Neural Processing Unit (NPU) capable of INT4/INT8/INT16 mixed-precision operations with 6.0TOPS computing power. The system supports dual PCIe M.2 AI expansion slots and compatibility with mainstream AI development tools and interfaces. Designed for industrial-grade wide-temperature environments (-40°C to +85°C), it incorporates 4000V high-voltage electrical isolation in expansion ports to ensure stable performance under extreme operating conditions. The display system supports LVDS, eDP, and MIPI outputs, along with HDMI 8K output and HDMI 4K input, enabling multi-screen display functionality. The network communication features three Gigabit Ethernet ports, dual-band 2.4G/5G Wi-Fi, Bluetooth 5.2, and supports 4G/5G modules with GPS positioning. The storage and expansion capabilities are comprehensive, including PCIe M.2, USB, and TF card slots, as well as UART, RS232, RS485, CAN, GPIO, I²C, gravity sensor, fan control, MIPI/USB camera, infrared remote control, and POE power supply interfaces, fully meeting the diverse needs of industrial smart terminals in complex scenarios such as AI inference, human-machine interaction, and device networking.

2. Characteristic

- High performance: The RK3588J industrial-grade octa-core 64-bit CPU processor delivers a clock speed of up to 2.4 GHz.
- High computing power: 6 Tops computing capacity with expandable GPUs, supporting multiple AI development tools and interfaces.
- High stability: The DI/DO/RS232/RS485/CAN interfaces feature 4000V full isolation.
- High voltage input: 9V to 36V DC voltage.
- Wide temperature range: The motherboard materials utilize industrial-grade components with a wide temperature range of -40 to 85 degrees Celsius.
- High definition: HDMI 8K output and HDMI 4K input.
- Highly integrated: Featuring multiple interface options including 3 Gigabit Ethernet ports, WIFI/BT, 4G/5G connectivity, GPS, 2 CAN bus channels, 4 RS485 ports, 2 RS232/RS485 ports, 2 DI channels, 2 DO channels, 4 USB ports, and POE expansion capabilities.
- Easy upgrades: Supports multiple upgrade methods including USB drives, TF cards, remote OTA, and computer USB cables.
- Extensive compatibility: Fully supports mainstream USB/serial devices including printers, card readers, password keyboards, fingerprint scanners, cameras, ID card readers, and QR code scanners, with demo test programs provided.

3. Product interface



3.1. Hardware specifications

| | |
|--------------------------------|--|
| operating system | Ubuntu22.04/Android12.0/Debian |
| processor CPU | Rockchip RK3588J (8nm LPP process) An 8-core processor with 64-bit ARM architecture, capable of reaching a maximum clock speed of 2.4GHz. Based on quad-core Cortex-A76 (large core) + quad-core Cortex-A55 (small core) |
| graphics processing unit GPU | Mali-G610 GPU MP4 Quad-Core GPU Supports OpenGL ES3.2, OpenVG 1.1, and OpenCL 2.2, with 450GFLOP precision floating-point operations |
| Neural Network Processor (NPU) | Equipped with a 6Tops neural network processor (NPU), supporting INT4/INT8/INT16/FP16 arithmetic operations and an external PCIE interface for M.2-packaged computing power cards. Supports models such as Caffe, Mxnet, TensorFlow, TF Lite, ONNX, and Darknet Provide AI development tools: enable rapid model conversion. |
| internal storage | LPDDR4 8GB (4G/8G/16G available) |
| memory | eMMC 128GB (available in 32 GB, 64 GB, 128 GB, or 256 GB options) |
| PCIE continuation | 2×PCIE M.2 expansion slots with 4 lanes for high-speed communication, compatible with M.2242 and M.2260 form factors, supports NVMe protocol, and features Gen4.0 x4 interfaces. |
| network | Supports 3 Ethernet ports with speeds of 10/100/1000 Mbps |
| | Supports dual-band WiFi (2.4G/5G) and Wi-Fi 802.11b/g/n/ac protocols (WiFi 6 optional). |
| | Supports Bluetooth functionality, including V2.1+EDR, Bluetooth 3.0, Bluetooth 3.0+HS, Bluetooth 4.1, Bluetooth 4.2, Bluetooth 5.2, and BLE. |
| | Supports 4G/5G (optional) |
| GPS navigation | Board-mounted GPS/BD module (optional) |
| picture orientation | Supports manual rotation at 0°,90°,180°, and 270°, and gravity-sensing auto-screen rotation (optional) |
| Display interface | 1 LVDS channel (dual-channel, 6-bit/8-bit), 1080P 60Hz output, power supply options: 3.3V/5V/12V 1*eDP (eDP1.3, 4 lanes with 5.4Gbps), powered by 3.3V/5V supply 1* HDMI 2.1, 8K,60Hz output |

| | |
|---------------------------------|---|
| | 1* HDMI 2.0, K 60Hz input 1*MiPi supports 5.7Gbps output) |
| Board-mounted backlight control | 12V backlight power supply |
| audio frequency | 1*Speaker output (2*18W 4R) 1* Earpiece output 2*Microphone input |
| camera | 1* MIPI camera input capability, supporting up to 48MP resolution (optional) Supports USB camera (optional) |
| RTC | External real-time clock power battery with on/off timer support |
| USB | 4*USB-2.0 HOST, 1*USB3.0 CPU, 1*USB3.0 OTG |
| PCIe | 1*Mini PCIe (for 4G/5G LTE) |
| SIM | 1*SIM card slot for Mini PCIe expansion of 4G/5G LTE modules |
| infrared | 1* Infrared receiver base, supporting infrared remote control function |
| LED | 1* Power status LED (red), * System LED (blue, default flashing) |
| key | 1*Reset button, *Power button, 1*Upgrade button |
| gorge line | 1*UART TTL, 4*RS485 (with 4000V isolation support), 2*RS232/RS485 (with 4000V isolation support) |
| IO mouth | 2 DO ports, 2 DI ports (supporting 4000V isolation) |
| CAN | 2 CAN ports (supporting 4000V isolation) |
| I2C port | 1*I2C port |
| Fan opening | Supports 5V/12V fan interface |
| POE | 1*POE interface |
| power input | DC9V~36V,5A (requires surge voltage below 14V and ripple voltage below 100mV), supports automatic startup upon power-up or manual activation via power button |
| working temperature | -40°C~85°C |
| Storage temperature | -40°C~85°C |
| Storage humidity | 10%~80% |
| Mainboard size | 170mm*140mm*20mm |
| multi-media | Supports 8K 60fps H.265/H.264 video decoding Supports 8K 30fps H.265/H.264 video encoding Supports same compilation and same solution |

3.3.Source

The spacing between power input interface sockets is 2.0 mm.

| order number | definition | attribute | description | |
|--------------|------------|------------|---------------------------|---|
| 1 | 9V~36V_IN | import | 9V~36V power supply input |  |
| 2 | 9V~36V_IN | import | 9V~36V power supply input | |
| 3 | NC | NC | barefoot | |
| 4 | GND | earth wire | earth wire | |
| 5 | GND | earth wire | earth wire | |

The distance between the output interface sockets is 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------|------------|-------------------------|--|
| 1 | GND | earth wire | earth wire |  |
| 2 | GND | earth wire | earth wire | |
| 3 | 12V_OUT | import | 12V power supply output | |
| 4 | 12V_OUT | import | 12V power supply output | |

3.4.Screen backlight

The LCD backlight jack socket spacing is 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------|------------|-------------------------|---|
| 1 | 12V | output | 12V power supply output |  |
| 2 | 12V | output | 12V power supply output | |
| 3 | LCD-BLON | output | Backlight control | |
| 4 | LCD-ADJ | output | Backlight adjustment | |
| 5 | GND | earth wire | earth wire | |
| 6 | GND | earth wire | earth wire | |

3.5.eDP

The eDP LCD jack socket has a spacing of 2.0mm between sockets.

| order number | definition | attribute | description | |
|--------------|------------|------------|-----------------------------|--|
| 1 | VCC | output | 3.3V/5V power supply output |  |
| 2 | VCC | output | | |
| 3 | GND | earth wire | earth wire | |
| 4 | GND | earth wire | earth wire | |
| 5 | D0- | output | data | |
| 6 | D0+ | output | data | |
| 7 | D1- | output | data | |
| 8 | D1+ | output | data | |
| 9 | D2- | output | data | |
| 10 | D2+ | output | data | |
| 11 | D3- | output | data | |
| 12 | D3+ | output | data | |
| 13 | GND | earth wire | earth wire | |
| 14 | GND | earth wire | earth wire | |
| 15 | AUX- | output | data | |
| 16 | AUX+ | output | data | |
| 17 | GND | earth wire | earth wire | |
| 18 | GND | earth wire | earth wire | |
| 19 | 3V3 | output | 3.3V power supply output | |
| 20 | HPD | import | HPD test foot | |

3.6.electric fan

The spacing between the fan jack sockets is 1.25mm.


| order number | definition | attribute | description | |
|--------------|------------|------------|-------------|---|
| 1 | PWM | output | PWM |  |
| 2 | NC | barefoot | NC | |
| 3 | VDD | output | 5V/12V | |
| 4 | GND | earth wire | earth wire | |

3.7.LVDS

The LVDS jack socket has a spacing of 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------|------------|--------------|--|
| 1 | POWER | output | 3.3V/5V/12V | |
| 2 | POWER | | power supply | |
| 3 | POWER | | output | |
| 4 | GND | earth wire | earth wire | |
| 5 | GND | | | |
| 6 | GND | | | |
| 7 | TA1- | output | data |  |
| 8 | TA1+ | output | data | |
| 9 | TB1- | output | data | |
| 10 | TB1+ | output | data | |
| 11 | TC1- | output | data | |
| 12 | TC1+ | output | data | |
| 13 | GND | earth wire | earth wire | |
| 14 | GND | | | |
| 15 | TCLK1- | output | clock | |
| 16 | TCLK1+ | output | clock | |
| 17 | TD1- | output | data | |
| 18 | TD1+ | output | data | |
| 19 | TA2- | output | data | |
| 20 | TA2+ | output | data | |
| 21 | TB2- | output | data | |
| 22 | TB2+ | output | data | |
| 23 | TC2- | output | data | |
| 24 | TC2+ | output | data | |
| 25 | GND | earth wire | earth wire | |
| 26 | GND | | | |
| 27 | TCLK2- | output | clock | |
| 28 | TCLK2+ | output | clock | |
| 29 | TD2- | output | data | |
| 30 | TD2+ | output | data | |

LVDS LCD JP JACK interface with 2.0mm socket spacing


| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------------|---|
| 1 | 3.3V | output | 3.3V output |  |
| 2 | LCD-VDD-IN | import | LCD voltage input | |
| 3 | 5V | output | 5V output | |

| | | | |
|---|------------|--------|-------------------|
| 4 | LCD-VDD-IN | import | LCD voltage input |
| 5 | 12V | output | 12V output |
| 6 | LCD-VDD-IN | import | LCD voltage input |

3.8.MIPI Camera

MIPI Camera jack spacing: 0.5mm

| order number | definition | attribute | description | |
|--------------|------------|------------|-------------|--|
| 1 | NC | barefoot | barefoot | |
| 2 | VDD28 | source | 2.8V output | |
| 3 | VDD13 | source | 1.3V output | |
| 4 | VDD18 | source | 1.8V output | |
| 5 | NC | barefoot | barefoot | |
| 6 | GND | earth wire | earth wire | |
| 7 | VDD28 | source | 2.8V output | |
| 8 | GND | earth wire | earth wire | |
| 9 | SDA | output | data | |
| 10 | SCL | output | clock | |
| 11 | RST | output | reset | |
| 12 | PWDN | output | enable bit | |
| 13 | GND | earth wire | earth wire | |
| 14 | MLCK | output | clock | |
| 15 | GND | earth wire | earth wire | |
| 16 | DP3 | output | data | |
| 17 | DN3 | output | data | |
| 18 | GND | earth wire | earth wire | |
| 19 | DP2 | output | data | |
| 20 | DN2 | output | data | |
| 21 | GND | earth wire | earth wire | |
| 22 | DP1 | output | data | |
| 23 | DN1 | output | data | |
| 24 | GND | earth wire | earth wire | |
| 25 | CLKP | output | clock | |
| 26 | CLKN | output | clock | |
| 27 | GND | earth wire | earth wire | |
| 28 | DPO | output | data | |
| 29 | DN0 | output | data | |
| 30 | GND | earth wire | earth wire | |



3.9. UART TTL

UART TTL interface (UART TTL jack) with 2.0mm pin pitch

| order number | definition | attribute | description | |
|--------------|------------|------------|---------------------|---|
| 1 | 3.3V | output | 3.3V output |  |
| 2 | TX6 | output | Send (TX6) ttyS6 | |
| 3 | RX6 | import | Receive (RX6) ttyS6 | |
| 4 | GND | earth wire | earth wire | |

3.10. Button/Remote Control

KEY/IR IN JACK 2.0MM

| order number | definition | attribute | description | |
|--------------|------------|------------|---------------------|--|
| 1 | 3.3V | output | 3.3V voltage output |  |
| 2 | IR | import | receive | |
| 3 | UBOOT | import | Upgrade key | |
| 4 | RST | import | reset key | |
| 5 | PWR | import | Power On/Off Key | |
| 6 | GND | earth wire | earth wire | |

3.11. DEBUG

JACK 3.5MM

| order number | definition | attribute | description | |
|--------------|------------|------------|-------------------|---|
| 1 | TX | output | transmit by radio |  |
| 2 | RX | import | receive | |
| 3 | GND | earth wire | earth wire | |

3.12. MIC

The microphone jack socket spacing is 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------|--|
| | | | | |

| order number | definition | attribute | description | |
|--------------|------------|------------|--------------------|---|
| 1 | MIC- | earth wire | earth wire |  |
| 2 | MIC+ | import | MIC positive input | |

3.13. suona

The speaker output jack socket spacing is 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------|-----------|---|---|
| 1 | LP | output | Positive output on the left channel |  |
| 2 | LN | output | Left channel output negative electrode | |
| 3 | RP | output | Right channel output positive pole | |
| 4 | RN | output | Right channel output negative electrode | |

3.14. I2C

The I2C interface (I2C JACK) socket spacing is 2.0mm.

| order number | definition | attribute | description | |
|--------------|------------------|------------|---------------------------|---|
| 1 | 3.3 V | output | 3.3V voltage output |  |
| 2 | INT (3.3V level) | import | external device interrupt | |
| 3 | RST (3.3V level) | output | Redeploy external devices | |
| 4 | SCL (3.3V level) | output | clock | |
| 5 | SDA (3.3V level) | output | data | |
| 6 | GND | earth wire | earth wire | |

3.15. USB

The USB2.0-HOST interface jack features a socket spacing of 2.0mm.

| order | definition | attribute | description |
|-------|------------|-----------|-------------|
|-------|------------|-----------|-------------|

| number | | | | |
|--------|-----|------------|-------------------|---|
| 1 | 5V | output | 5V voltage output |  |
| 2 | DM | import | DM- | |
| 3 | DP | import | DP+ | |
| 4 | GND | earth wire | earth wire | |

3.16. RTC

3V button battery socket (BAT JACK) with 1.25mm spacing

| order number | definition | attribute | description | |
|--------------|------------|------------|-------------|---|
| 1 | BAT+ | import | 3V input |  |
| 2 | GND | earth wire | earth wire | |

3.17. CAN

CAN interface (CAN JACK) with 2x3.5mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|------------------|------------------|---|
| 1 | CAN1H | data | data |  |
| 2 | CAN1L | data | data | |
| 3 | GND | simulated ground | simulated ground | |
| 4 | CAN2H | data | data | |
| 5 | CAN2L | data | data | |
| 6 | GND | simulated ground | simulated ground | |

CAN interface (CAN JACK) with 2.0mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|------------------|------------------|---|
| 1 | CAN1H | data | data |  |
| 2 | CAN1L | data | data | |
| 3 | CAN2H | data | data | |
| 4 | CAN2L | data | data | |
| 5 | GND | simulated ground | simulated ground | |

3.18. RS232/RS485

RS232/RS485 interface (RS232/RS485 JACK) with 2x3.5mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|--------------|------------------|-------------------|---|
| 1 | TX1/RS485-A5 | output | Transmit (TX1/A5) |  |
| 2 | RX1/RS485-B5 | import | Receive (RX1/B5) | |
| 3 | GND | simulated ground | simulated ground | |
| 4 | TX2/RS485-A6 | output | Transmit (TX2/A6) | |
| 5 | RX2/RS485-B6 | import | Receive (RX2/B6) | |
| 6 | GND | simulated ground | simulated ground | |

RS232/RS485 interface (RS232/RS485 JACK) with 2.0mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|--------------|------------------|-------------------|---|
| 1 | TX1/RS485-A5 | output | Transmit (TX1/A5) |  |
| 2 | RX1/RS485-B5 | import | Receive (RX1/B5) | |
| 3 | TX2/RS485-A6 | output | Transmit (TX2/A6) | |
| 4 | RX2/RS485-B6 | import | Receive (RX2/B6) | |
| 5 | GND | simulated ground | simulated ground | |


3.19. RS485

RS485 interface (RS485 JACK) with 2x3.5mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------|---|
| 1 | RS485-A3 | output | Send (A3) |  |

| | | | | |
|---|----------|---------------------|-------------------|--|
| 2 | RS485-B3 | import | Receive (B3)ttyS8 | |
| 3 | GND | simulated ground | simulated ground | |
| 4 | RS485-A4 | output | Send (A4) ttyS9 | |
| 5 | RS485-B4 | import | Receive (B4)ttyS9 | |
| 6 | GND | simulated ground | simulated ground | |

RS485 interface (RS485 JACK) with 2.0mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|---------------------|-------------------|---|
| 1 | RS485-A3 | output | Send (A3)ttyS8 |  |
| 2 | RS485-B3 | import | Receive (B3)ttyS8 | |
| 3 | RS485-A4 | output | Send (A4) ttyS9 | |
| 4 | RS485-B4 | import | Receive (B4)ttyS9 | |
| 5 | GND | simulated ground | simulated ground | |

RS485 interface (RS485 JACK) with 2x3.5mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|---------------------|-------------------|---|
| 1 | RS485-A1 | output | Send (A1) ttyS0 |  |
| 2 | RS485-B1 | import | Receive (B1)ttyS0 | |
| 3 | GND | simulated ground | simulated ground | |
| 4 | RS485-A2 | output | Send (A2) ttyS3 | |
| 5 | RS485-B2 | import | Receive (B2)ttyS3 | |
| 6 | GND | simulated ground | simulated ground | |

RS485 interface (RS485 JACK) with 2.0mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|---------------------|-------------------|---|
| 1 | RS485-A1 | output | Send (A1) ttyS0 |  |
| 2 | RS485-B1 | import | Receive (B1)ttyS0 | |
| 3 | RS485-A2 | output | Send (A2) ttyS3 | |
| 4 | RS485-B2 | import | Receive (B2)ttyS3 | |
| 5 | GND | simulated ground | simulated ground | |

3.20. IO

IO JACK with 2x3.5mm pin spacing (interface equipped with isolation)

| order number | definition | attribute | description | |
|--------------|------------|-------------------------|--------------------------------|---|
| 1 | DO1 | data | data | |
| 2 | COM1 | data | data | |
| 3 | DO2 | data | data | |
| 4 | COM2 | data | data | |
| 5 | 12V/GND | Output/Analog Ground | 12V output/analog ground |  |
| 6 | DI1 | data | data | |
| 7 | 12V/GND | Output/Analog Ground | 12V output/analog ground | |
| 8 | DI2 | data | data | |

IO JACK with 2.0mm socket spacing (interface equipped with isolation)


| order number | definition | attribute | description | |
|--------------|------------|-------------------------|--------------------------------|---|
| 1 | 12V/GND | Output/Analog Ground | 12V output/analog ground |  |
| 2 | DI1 | data | data | |
| 3 | 12V/GND | Output/Analog Ground | 12V output/analog ground | |
| 4 | DI2 | data | data | |
| 5 | COM2 | data | data | |
| 6 | DO2 | data | data | |
| 7 | COM1 | data | data | |
| 8 | DO1 | data | data | |

3.21. RJ45


RJ45-3 jack socket spacing: 2x2.0mm

| order number | definition | attribute | description |
|--------------|------------|-----------|-------------|
|--------------|------------|-----------|-------------|


| | | | |
|----|------|--------|-------------|
| 1 | Y+_3 | output | Yellow LED+ |
| 2 | Y-_3 | output | Yellow LED- |
| 3 | D-_3 | import | data |
| 4 | D+_3 | import | data |
| 5 | B-_3 | import | data |
| 6 | C-_3 | import | data |
| 7 | C+_3 | import | data |
| 8 | B+_3 | import | data |
| 9 | A-_3 | import | data |
| 10 | A+_3 | import | data |
| 11 | G-_3 | output | Green LED- |
| 12 | G+_3 | output | Green LED+ |



RJ45-2 jack socket spacing: 2x2.0mm

| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------|---|
| 1 | Y+_2 | output | Yellow LED+ |  |
| 2 | Y-_2 | output | Yellow LED- | |
| 3 | D-_2 | import | data | |
| 4 | D+_2 | import | data | |
| 5 | B-_2 | import | data | |
| 6 | C-_2 | import | data | |
| 7 | C+_2 | import | data | |
| 8 | B+_2 | import | data | |
| 9 | A-_2 | import | data | |
| 10 | A+_2 | import | data | |
| 11 | G-_2 | output | Green LED- | |
| 12 | G+_2 | output | Green LED+ | |


RJ45-1 jack socket spacing: 2x2.0mm

| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------|---|
| 1 | Y+_1 | output | Yellow LED+ |  |
| 2 | Y-_1 | output | Yellow LED- | |
| 3 | D-_1 | import | data | |
| 4 | D+_1 | import | data | |
| 5 | B-_1 | import | data | |
| 6 | C-_1 | import | data | |
| 7 | C+_1 | import | data | |

| | | | | |
|----|------|--------|------------|--|
| 8 | B+_1 | import | data | |
| 9 | A-_1 | import | data | |
| 10 | A+_1 | import | data | |
| 11 | G-_1 | output | Green LED- | |
| 12 | G+_1 | output | Green LED+ | |

3.22. FPC MiPi LCD


FPC MiPi LCD jack with 0.3mm spacing between sockets (bottom layer)

| order number | definition | attribute | description | |
|--------------|------------|------------|-----------------|---|
| 1 | LED+ | output | backlight anode | |
| 2 | LED+ | | | |
| 3 | LED+ | | | |
| 4 | GND | earth wire | earth wire | |
| 5 | LED- | output | Backlight anode | |
| 6 | LED- | | | |
| 7 | LED- | | | |
| 8 | LED- | | | |
| 9 | GND | earth wire | earth wire | |
| 10 | GND | | | |
| 11 | MiPi2+ | output | data |  |
| 12 | MiPi 2- | output | data | |
| 13 | GND | earth wire | earth wire | |
| 14 | MiPi 1+ | output | data | |
| 15 | MiPi 1- | output | data | |
| 16 | GND | earth wire | earth wire | |
| 17 | MiPi CLK+ | output | clock | |
| 18 | MiPi CLK- | output | clock | |
| 19 | GND | earth wire | earth wire | |
| 20 | MiPi 0+ | output | data | |
| 21 | MiPi 0- | output | data | |
| 22 | GND | earth wire | earth wire | |
| 23 | MiPi 3+ | output | data | |
| 24 | MiPi 3- | output | data | |
| 25 | GND | earth wire | earth wire | |
| 26 | NC | NC | NC | |
| 27 | RESET | output | reset | |
| 28 | NC | NC | NC | |

| | | | | |
|----|-----------|--------|---------|--|
| 29 | VDDIO1.8V | output | VDD1.8V | |
| 30 | VDD3.3V | output | VDD3.3V | |
| 31 | VDD3.3V | output | VDD3.3V | |

3.23. POE

POE interface (POE JACK) socket spacing: 1.25mm (bottom layer) (optional)

| order number | definition | attribute | description | |
|--------------|------------|-----------|-------------|---|
| 1 | POE7-8 | import | Input 7-8 |  |
| 2 | POE4-5 | import | 4-5 inputs | |
| 3 | POE3-6 | import | Input 3-6 | |
| 4 | POE1-2 | import | Input 1-2 | |